

Preset command functions chart for Ratingsecu IP speed dome camera



These three buttons respectively represent: **Set preset, delete preset, call preset.**

Preset	Function	Preset	Function
Set No. 35 Preset	Left limit position	Call No.34 preset	Seeking reference point
Set No. 36 Preset	Right limit position	Call No.38 preset	Limit scan and auto scan
Set No. 38 Preset	Delete limit scan	Call No.39 preset	auto scan
Set No. 40 Preset	Delete all presets	Call No.40 preset	Delete alarm
Set No. 41 Preset	Delete No.1 Tour scan route	Call No.41 preset	Run tour scan 1—16 preset
Set No. 42 Preset	Delete No.2 Tour scan route	Call No.42 preset	Run tour scan 17—32 preset
Set No. 43 Preset	Delete No.3 Tour scan route	Call No.43 preset	Run tour scan 65—80 preset
Set No. 44 Preset	Delete No.4 Tour scan route	Call No.44 preset	Run tour scan113—128preset
Set No. 45 Preset	Delete No.5 Tour scan route	Call No.45 preset	Run tour scan129—144preset
Set No. 46 Preset	Delete No.6 Tour scan route	Call No.46 preset	Run tour scan145—160preset
Set No. 47 Preset	Delete No.7 Tour scan route	Call No.47 preset	Run tour scan161—176preset
Set No. 48 Preset	Delete No.8 Tour scan route	Call No.48 preset	Run tour scan177—192preset
Set No. 49 Preset	Close flip horizontal function	Call No.49 preset	Open flip horizontal function
Set No. 50 Preset	Decrease ir led photosensitive factor (led will be on earlier)	Call No.50 preset	increase ir led photosensitive factor (led will be on later)
Set No. 51 Preset	Preset residence time 2S	Call No.56 preset	Open monitoring position function
Set No. 52 Preset	Preset residence time 4S	Call No.58 preset	Call monitoring position
Set No. 53 Preset	Preset residence time 6S	Call 59/95 preset	Enter main menu
Set No. 54 Preset	Preset residence time 8S	Call 60 preset	Open Proportional variable speed
Set No. 55 Preset	Preset residence time 10S	Call 100 preset	Switch of open and close alarm
Set No. 56 Preset	Close monitoring position function	Set No. 181 Preset	The first alarm set
Set No. 58 Preset	Set monitoring position	Set No. 182 Preset	The second alarm set
Set No. 60 Preset	close Proportional variable speed	Set No. 200 Preset	Delete password(high speed)
Set No. 61 Preset	Scan speed 9 degree/S	Set No. 201 Preset	sony
Set No. 62 Preset	Scan speed 15/20 degree/S	Set No. 204 Preset	New LG
Set No. 63 Preset	Scan speed 20/30 degree/S	Set No. 205 Preset	CNB
Set No. 64 Preset	Scan speed 30/50degree/S	Set No. 206 Preset	Samsung
Set No. 264 Preset	Manually setting multiple of turning lights	Set No. 253 Preset	All RTS zoom module